

6 EYES RGB MOVING LASER BAR LIGHT PRODUCT MANUAL




Thank you for using the RGB animation laser projector. For the sake of safety and better operation of this projector, please read this manual carefully before use and operation, lest incur any personal injury or damage to the projector.

The series of products for the standard carton packaging, can choose and buy air packing, please read this manual carefully before using, according to the rules of operation, to avoid the damage of light or physical harm, please after receipt of the product after careful processing, check whether product transport damaged, open the lid, take out the the related attachment in the oven, take out the lamps and lanterns, place the lamps and lanterns in a level table, for the relevant operation.

Note: do not squeeze the plastic parts to avoid cracking or deformation. Check the accessories as follows: One laser lamp, one power cord, one user's manual, one hanger and one set.


Installation instructions

1. When installing the equipment, please ensure that there are no inflammable and explosive articles (decorations, etc.) within the range of at least 2.5 meters, and ensure that the space between the lamp and the wall is more than 0.5 meters.
2. Before installation, please confirm whether the power supply voltage you use is consistent with the voltage marked by the lamp.
3. Please make sure that the ventilation fan and exhaust passage are not blocked by other equipment or decorative materials, such as newspapers, tablecloths and curtains
4. The equipment shall be fixed and installed. To ensure the stability of its mounting point, it should be able to bear at least 10 times of the weight of the product.
5. For security reasons, the unit should be connected to the main socket with ground wire.



STARSHINE LIGHTS
PRODUCT MANUAL





STARSHINE LIGHTS PRODUCT MANUAL



LED DISPLAY



Function Up Down Enter

Menu function:

- | | |
|----------------------------|--|
| 1. DMX Address | A001---A512 ,address code |
| 2. Show Mode | SOUND AUTO, effect selection |
| 3. Slave Mode | MASTER, SLAVE, selection |
| 4. Black Out | YES, NO ,standby mode |
| 5. Sound State | ON, OFF |
| 6. Sound Sense sensitive) | sound sensitivity (0 is off, 100 is most |
| 7. Pan Inverse | YES, NO, horizontal reverse |
| 8. Tilt1 Inverse | YES, NO, vertical reverse |
| 9. Tilt2 Inverse | YES, NO, vertical reverse |
| 10. Tilt3 Inverse | YES, NO,vertical reverse |
| 11. Tilt4 Inverse | YES, NO,vertical reverse |
| 12. Tilt5 Inverse | YES, NO,vertical reverse |
| 13. Tilt6 Inverse | YES, NO,vertical reverse |
| 14. Back Light | ON, OFF,background light switch |
| 15. Auto Test | Auto testing |
| 16. Fixture Time | 0----9999 machine light |
| 17. Firmware Version | V104, software version number |
| 18. Defaults | YES, NO,factory data reset |
| 19. System Reset | YES, NO, the machine is reset |



STARSHINE LIGHTS PRODUCT MANUAL



DMX channel function

1. 11CH:

channel	value	function
CH1	001 - 255	ALL Laser Dimmer channel
CH2	001 - 255	Flash channel,0-9 no flash,10-255 flash and speed
CH3	001 - 255	X motor angle selection
CH4	001 - 255	X motor speed
CH5	0---15	0---55 non-function
	16---80	Auto effect 1 (only motor effect,need add)
	81---105	Auto effect 2 (XY is uncontrollable)
	106---130	Auto effect 3 (XY is uncontrollable)
	131---155	Auto effect 4 (XY is uncontrollable)
	156---180	Auto effect 5 (XY is uncontrollable)
	181---205	Sound control (XY is uncontrollable)
	206---230	Auto effect 6 (XY is uncontrollable)
	231---255	Sound control(XY is uncontrollable)
CH6	000-255	Auto effect speed
CH7	000-015	Light off
	016-035	Color effect chasing 1
	036-056	Color effect chasing 2
	057-076	Color effect chasing 3
	077-097	Color effect chasing 4
	098-243	Color effect chasing 5--20
	244-255	All on
CH8	001 - 255	Color chasing from slow to fast (only work in CH5 ,value 015-117)
CH9	001 - 255	Y1-6 motor angle selection
CH10	001 - 255	Y1-6 motor speed
CH11	0-249	Non function
	250-255	Stay 5sec motor reset

2.26CH:

channel	value	function
CH1	001 - 255	ALL Laser Dimmer channel
CH2	001 - 255	Flash channel,0-9 no flash,10-255 flash and speed
CH3	001 - 255	X motor angle selection
CH4	001 - 255	X motor speed
CH5	0---15	0---55 non-function
	16---80	Auto effect 1 (only motor effect,need add)
	81---105	Auto effect 2 (XY is uncontrollable)
	106---130	Auto effect 3 (XY is uncontrollable)
	131---155	Auto effect 4 (XY is uncontrollable)
	156---180	Auto effect 5 (XY is uncontrollable)
	181---205	Sound control (XY is uncontrollable)
	206---230	Auto effect 6 (XY is uncontrollable)
CH6	231---255	Sound control(XY is uncontrollable)
	000-255	Auto effect speed
	000-015	Light off
	016-035	Color effect chasing 1
	036-056	Color effect chasing 2
	057-076	Color effect chasing 3
	077-097	Color effect chasing 4
	098-243	Color effect chasing 5--20
244-255	All on	
CH7	001 - 255	Color chasing from slow to fast (only work in CH5 ,value 015-117)
CH8	001 - 255	Y1-6 motor angle selection
CH9	001 - 255	Y1-6 motor speed
CH10	000-255	Red laser 1-6 dimmer channel
CH11	000-255	Green laser 1-6 dimmer channel
CH12	000-255	Blue laser 1-6 dimmer channel
CH13	000-255	



STARSHINE LIGHTS PRODUCT MANUAL





STARSHINE LIGHTS PRODUCT MANUAL

CH14	000-255	Y1 Motor angle
CH15	001-255	RGB1 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH16	000-255	Y2 Motor angle
CH17	001-255	RGB2 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH18	000-255	Y3 Motor angle
CH19	001-255	RGB3 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH20	000-255	Y4 Motor angle
CH21	001-255	RGB4 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH22	000-255	Y5 Motor angle
CH23	001-255	RGB5 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH24	000-255	Y6 Motor angle
CH25	001-255	RGB6 channel,0-31 close,32-63red,64-95green,96-127blue,128-159yellow,160-191RB,192-223GB,224-255RGB
CH26	0-249	Non function
	250-255	Stay 5sec motor reset



3.38CH:

channel	value	function
CH1	001 - 255	ALL Laser Dimmer channel
CH2	001 - 255	Flash channel,0-9 no flash,10-255 flash and speed
CH3	001 - 255	X motor angle selection
CH4	001 - 255	X motor speed
CH5	0---55	0---55 non-function
	56---80	Auto effect 1 (only motor effect,need add)
	81---105	Auto effect 2 (XY is uncontrollable)
	106---130	Auto effect 3 (XY is uncontrollable)
	131---155	Auto effect 4 (XY is uncontrollable)
	156---180	Auto effect 5 (XY is uncontrollable)
	181---205	Sound control (XY is uncontrollable)
	206---230	Auto effect 6 (XY is uncontrollable)
CH5	231---255	Sound control(XY is uncontrollable)
CH6	000-255	Auto effect speed
CH7	000-015	Light off
	016-035	Color effect chasing 1
	036-056	Color effect chasing 2
	057-076	Color effect chasing 3
	077-097	Color effect chasing 4
	098-243	Color effect chasing 5--20
	244-255	All on
CH8	001 - 255	Color chasing from slow to fast (only work in CH5 ,value 015-117)
CH9	001 - 255	Y1-6 motor angle selection
CH10	001 - 255	Y1-6 motor speed
CH11	000-255	Red laser 1-6 dimmer channel
CH12	000-255	Green laser 1-6 dimmer channel
CH13	000-255	Blue laser 1-6 dimmer channel



STARSHINE LIGHTS PRODUCT MANUAL





STARSHINE LIGHTS PRODUCT MANUAL



CH13	000-255	Blue laser 1-6 dimmer channel
CH14	000-255	Y1 Motor angle
CH15	000-255	Y1 Laser Red laser channel
CH16	000-255	Y1 Laser Green laser channel
CH17	000-255	Y1 Laser Blue laser channel
CH18	000-255	Y2 Motor angle
CH19	001-255	Y2 Laser Red laser channel
CH20	000-255	Y2 Laser Green laser channel
CH21	001-255	Y2 Laser Blue laser channel
CH22	000-255	Y3 Motor angle
CH23	001-255	Y3 Laser Red laser channel
CH24	000-255	Y3 Laser Green laser channel
CH25	001-255	Y3 Laser Blue laser channel
CH26	000-255	Y4 Motor angle
CH27	001-255	Y4 Laser Red laser channel
CH28	000-255	Y4 Laser Green laser channel
CH29	001-255	Y4 Laser Blue laser channel
CH30	000-255	Y5 Motor angle
CH31	001-255	Y5 Laser Red laser channel
CH32	000-255	Y5 Laser Green laser channel
CH33	001-255	Y5 Laser Blue laser channel
CH34	000-255	Y6 Motor angle
CH35	001-255	Y6 Laser Red laser channel
CH36	000-255	Y6 Laser Green laser channel
CH37	001-255	Y6 Laser Blue laser channel
CH38	0-249	Non function
	250-255	Stay 5sec motor reset



STARSHINE LIGHTS PRODUCT MANUAL



Maintenance

It is very important to keep this RGB animation laser light clean, therefore please clean Dust-proof glass monthly to keep the lights away from dust, dirt or fog juice.

warned

Do not look directly at the light source when switching on. Make sure the power is cut off before any installation and maintenance work.

statement

This product when leaving the factory, the performance is good, the packing is complete. All users shall strictly abide by the warning and operation instructions stated above. Any damage caused by misuse is not covered by the warranty of the company, and the failure and problems caused by ignoring the operation manual are also covered by the dealer.