


Six Arms KING KONG Light PRODUCT MANUAL



STARSHINE LIGHTS PRODUCT MANUAL



Thank you very much for purchasing six arms king kong light. For your personal safety and better use of this product, please read this manual carefully before use and follow the instructions to avoid personal injury and damage the lamp.

Technical parameters:

Power supply: AC90~240V, 50Hz/60Hz

Rated power: 150W

Lamp bead parameters: 10 CREE 10W RGB lamp beads, 50mW red green laser

Control mode: international DMX512, 22 channels

Dimming mode: 0~100% super smooth dimming

Working mode: DMX512, master/slave, self-propelled, voice control

Strobe: 20 times/second

Packing method: air case/carton

Inner box size: 35 * 35 * 22cm

Carton size: 73 * 37 * 46cm (4 PCS/carton)

N.W: 3.6KG

G.W: 4.32KG

Carton weight: 18.28KG

Instructions for use:

After opening the box, carefully check whether the lamp is damaged due to transportation, such as whether the screws are loose, whether the lens is broken, etc. Please check before powering on. Check whether the lamp is placed in the correct and stable position, and check whether the power supply voltage is the same as that of this product. This equipment belongs to Class 1 protection equipment, so the ground wire of the power supply must be grounded and completed by professionals. Check whether the power supply voltage is normal before use.





STARSHINE LIGHTS PRODUCT MANUAL

Display function:

This product adopts display mode operation mode and DMX mode operation mode, the specific settings are as follows:

addr	A001-A512	Set 512 address
Chnd	22ch	Display the number of channels
Shou (running mode)	d512	DMX512 mode
	auto	Self-propelled mode
	sond	Audio Mode
Sens	0-100	Voice control zero density setting
LED	oFF	The display is always on
	on	Show Sleep
Disp	OFF	Show Forward
	ON	Show Reverse
rst	Yes/no	Manual reset

Care and maintenance:

1. Do not keep your eyes facing the semiconductor light-emitting body for a long time, so as not to hurt your eyes;
2. Try to prevent dust, dirt and e-liquid from being artificially laid or even flowing into the lamp body, and keep the product as clean as possible in the use environment;
3. Please use professional glass cleaner regularly every month and clean the lens with flannel to ensure maximum brightness output and prolong the service life of the light source.

Special precautions for installation:

All lamps suspended, hung, fixed at height and laid horizontally must be secured with safety ropes or other means for the second time in addition to the normal light hook during installation to prevent falling and injuring people. The installation process without the second safety fixation has potential safety hazards and cannot be accepted.





STARSHINE LIGHTS PRODUCT MANUAL



DMX channel function

This product adopts standard DMX-512 signal and has 22 control channels in total. The specific control content is as follows:

22 Channel	Function	DMX value	Description
1	X-axis motor	0-255	0-255 0-540 degree rotation
2	X-axis motor speed	0-255	0-255 speed from fast to slow
3	Bee eye motor	0-255	0-128 0~180 degree rotation; 128-191 Stepless forward rotation; 192-255 Stepless reverse
4	Motor 1	0-255	0~180 degree rotation
5	Motor 2	0-255	0~180 degree rotation
6	Motor 3	0-255	0~180 degree rotation
7	Motor 4	0-255	0~180 degree rotation
8	Motor 5	0-255	0~180 degree rotation
9	Motor 6	0-255	0~180 degree rotation
10	General dimming	0-255	Linear dimming from dark to light
11	Strobe	0-9	No function
		10-255	Slow to fast
12	Bee eye red	0-255	Red dimming 0-100
13	Bee eye green	0-255	Green dimming 0-100
14	Bee eye blue	0-255	Blue dimming 0-100
15	Bee eye white	0-255	White dimming 0-100
16	Beam red	0-255	Red dimming 0-100
17	Beam green	0-255	Green dimming 0-100
18	Beam blue	0-255	Blue dimming 0-100
19	Beam white	0-255	White dimming 0-100
20	Red laser	0-255	Red dimming 0-100
21	Green laser	0-255	Green dimming 0-100
22	Macro function control	0-50	Valid from channel 1 to channel 21
		51-150	Random self walking
		150-250	Voice controlled self-propelled
		251-255	3 second reset